



CHB200W-110S SERIES

200 WATT 4:1 INPUT DC-DC CONVERTERS



FEATURES

- 200W Isolated Output
- Efficiency to 91%
- Low No Load Power Consumption
- Fixed Switching Frequency
- 4:1 Input Range
- Regulated Outputs
- Input Under-Voltage Protection
- Over Temperature Protection
- Over Voltage/Current Protection
- Remote On/Off
- Half-Brick Size Meet Industrial Standard
- UL60950-1 2nd (Basic Insulation) Approval
- Meet EN50155 with External Circuits
- Shock & Vibration Meet EN50155 (EN61373)
- Fire & Smoke Meet EN45545-2
- 5000m Operating Altitude
- Safety Meets IEC/EN/UL 62368-1



MODEL NUMBER	INPUT VOLTAGE	OUTPUT VOLTAGE	OUTPUT CURRENT		INPUT CURRENT		% EFF. (2)	CAPACITOR LOAD MAX.
			MIN.	MAX.	NO LOAD	FULL LOAD		
CHB200W-110S05	43-160 VDC	5 VDC	0 mA	40 A	10 mA	2043 mA	89	40000uF
CHB200W-110S12	43-160 VDC	12 VDC	0 mA	16.7 A	10 mA	2002 mA	91	16700uF
CHB200W-110S24	43-160 VDC	24 VDC	0 mA	8.3 A	10 mA	2034 mA	89	8300uF
CHB200W-110S28	43-160 VDC	28 VDC	0 mA	7.14 A	10 mA	2042 mA	89	7140uF
CHB200W-110S48	43-160 VDC	48 VDC	0 mA	4.2 A	10 mA	2014 mA	91	3000uF

NOTE:

1. Nominal Input Voltage 110 VDC.
2. Measure at Nominal Input Voltage.

