


## **SMD Schottky Rectifiers**

Primary characteristics					
Parameter	Value	Unit			
Maximum repetitive peak reverse voltage	20 ~ 100	V			
Maximum average forward rectified current	1.0	А			

## **Features**

- SMA (DO-214AC) case for easy automatic insertion.
- Pb-free and RoHS compliant
- Ultrafast reverse recovery time
- Low power loss, high efficiency
- High forward surge current capability
- High temperature soldering guaranteed: 260°C/10 seconds at terminals




Absolute maximum ratings and general electrical characteristics (T <sub>a</sub> = 25°C)										
Parameter		Symbol	Value						Unit	
		Symbol	SS12	SS13	SS14	SS15	SS16	SS18	SS110	Unit
Maximum repetitive peak reverse voltage		$V_{RRM}$	20	30	40	50	60	80	100	
Maximum RMS voltage		$V_{RMS}$	14	21	28	35	42	56	70	V
Maximum DC blocking voltage		$V_{DC}$	20	30	40	50	60	80	100	
Maximum average forward rectified current		I <sub>F(AV)</sub>	1.0							
Peak forward surge current 8.3mS single half sine wave superimposed on rated load (JEDEC method)		I <sub>FSM</sub>	40					A		
Maximum instantaneous forward voltage @I <sub>F</sub> =1.0A <sup>2)</sup>		V <sub>F</sub>	0.50 0.55 0.70		0.85		V			
Reverse current @V <sub>R</sub> =V <sub>DC</sub>	T <sub>a</sub> =25°C		0.5					mA		
	T <sub>a</sub> =100°C	I <sub>R</sub>	5.0							
Voltage rate of change (rated V <sub>R</sub> )		dv/dt	10000						V/µs	
Thermal resistance from junction to lead <sup>1)</sup>		R <sub>eJL</sub>	35					°C/W		
Operating junction and storage temperature range		Т <sub>ј</sub> , Т <sub>STG</sub>	-65 ~ 125					°C		


## Notes:

- 1) Mounted on PCB with 0.2 x 0.2" (5.0 x 5.0 mm) copper pad areas
- 2) Pulse test: 300µs pulse width, 1% duty cycle









Ordering information					
Part Number	Package	<b>Shipping Quantity</b>	Dimensions		
SS12 ~ SS110	SMA (DO-214AC)	2 000 pcs / 7" reel			

## **Disclaimer**

Akyga semi reserves the right to make changes without notice to any product specification herein, to make corrections, modifications, enhancements or other changes. Akyga semi or anyone on its behalf assumes no responsibility or liability for any errors or inaccuracies. Data sheet specifications and its information contained are intended to provide a product description only. "Typical" parameters which may be included on Akyga semi data sheets and/ or specifications can and do vary in different applications and actual performance may vary over time. Akyga semi does not assume any liability arising out of the application or use of any product or circuit. Akyga semi products are not designed, intended or authorized for use in medical, life-saving implant or other applications intended for life-sustaining or other related applications where a failure or malfunction of component or circuitry may directly or indirectly cause injury or threaten a life without expressed written approval of Akyga semi. Customers using or selling Akyga semi components for use in such applications do so at their own risk and shall agree to fully indemnify Akyga semi and its subsidiaries harmless against all claims, damages and expenditures.

Akyga semi Page 3/3 2023-09; REV. 1